

Keyless Entry for a 1993 964

© 2005 Directed Electronics, Inc.

Beneath Passenger Seat

Valet Switch

LED

DEI-712T

LIGHT FLASH JUMPER

ANTENNA - Do Not Cut!

- VIOLET Unlock #87 Normally Open (Input) 9
- RED/WHITE (-) Output of Channel 2 18
- BLUE/BLACK Unlock #30 Common Output 8
- BROWN/BLACK Unlock #87A Normally Closed 17
- VIOLET/BLACK Lock #87 Normally Open (Input) 7
- ORANGE (-) 500 mA Ground-When-Armed Output 16
- WHITE/BLACK Lock #87 Normally Closed 6
- YELLOW (+) Switched Ignition Input (Accessory) 15
- GREEN/BLACK Lock #30 Common Output 5
- WHITE/BLUE (-) 200 mA Channel 3 Validity Output 14
- BLACK/WHITE Output of Domelight Supervision Relay #87 4
- LT. GREEN/BLACK Factory Alarm Disarm 13
- BLACK/WHITE-1 Input of Domelight Supervision Relay #87 3
- BROWN (-) Horn Honk Output 12
- BLUE (-) 200mA 2nd Unlock Output 2
- BLACK (-) Chassis Ground Input 11
- RED (+) 12V Constant Power Input 1
- WHITE (+/-) Light Flash Output 10

Not Used

Not Used

Not Used

Not Used

Not Used

Not Used

Not Used

Not Used

Brown/Green

Brown/Blue

Brown/White

Black

Red

Black/White

Black/Green

All dashed lines represent 964 harness wires into which the DEI-712T wires are tapped.

928 618 260 00

Set jumper to (+)

Rectifier Diodes, Radio Shack P/N 276-1661